

Triplexer for Two Mobile Telephones (144-175 MHz (COM1) / 880-2300 MHz (COM2)) and Car Radio (0-108

DESCRIPTION

- Triplexer for simultaneous operation of two mobile telephones and car radio on a common mobile telephone antenna.
- Excellent coverage of the two bands 144 175 MHz and 880 2300 MHz.
- Extremely small dimensions.
- Quick installation using dual-adhesive pad provided.
- > FME-connections on antenna and transceiver terminals
 - CRC (M10 x 0.75) connection on the car radio terminal.
- 1 m or 5 m Procom 75 Ohm car radio cable available as an option.




ORDERING

Туре	Product No.
TRI 2/900/1800/UMTS/FM	200000792

ADDITIONAL DATA



TYPICAL RESPONSE CURVES



SPECIFICATIONS

Electrical	
Model	TRI 2/900/1800/UMTS/FM
Frequency	Mobile telephone 1 : 144 - 175 MHz (COM1) Mobile telephone 2 : 880 - 2300 MHz (COM2) Car radio : 0 - 108 MHz (RADIO)
Insertion Loss	0 - 108 MHz : = 1.5 dB 144 - 175 MHz : = 1.0 dB 880 - 2300 MHz : = 0.7 dB
Impedance	Transceiver : 50Ω Car radio : 75Ω
Isolation	COM1 to COM2 = 40 dB COM1 to car radio = 35 dB COM2 to car radio = 40 dB
Maximum Input Power	35 W mobile telephone

Mechanical	
Connection(s)	COM1, COM2, Antenna: FME Car radio: CRC-Connector (M10 x 0.75)
Dimensions	50 x 21 x 60 mm
Weight	0.068 kg / 0.15 lb
Accessories	Car radio cable Type 1 m CRC (length 1 m) Type 5 m CRC (length 5 m)

Environmental		
Operating Temperature Range	-30°C to +70°C	

INSTALLATION NOTES

- The 50 ♦ cable between antenna and diplexer should be kept as short as possible (preferably not more than 1 m).
- Some communication antennas have insufficient height to ensure satisfactory broadcast reception. Only antenna whips with a height of at least 25 cm are acceptable.
- Tuning: The antenna is tuned for best SWR at the operating frequency as usual. The filter is factory-tuned and ready for installation.