



X5000: 144/430/1200MHz(2m/70cm/23cm)

Length:1.8m / Radia length: approx.19cm / Weight:0.9kg

Gain:4.5dB(144MHz),8.3dB(430MHz),11.7dB(1200MHz)

Max.power rating:100W FM(Total) / Impedance:50ohms

VSWR:Less than 1.5:1 / Rated wind velocity:60m/sec.

Mast diameter accepted:30mm to 62mm / Connector:N-J

Type:6/8wave C-Load(144MHz),3x5/8wave C-Load(430MHz),7x5/8wave C-Load(1200MHz),FRP ouetshell