



X6000: 144/430/1200MHz(2m/70cm/23cm)

Length:3.05m / Radial length:approx.52cm / Weight:1.8kg

Gain:6.5dB(144MHz),9.0dB(430MHz),10.0dB(1200MHz)

Max. power rating:100W FM(144/430MHz),60W FM(1200MHz),Total 100W FM

Impedance:50ohms / VSWR :Less than 1.5:1

Rated wind velocity:50m/sec.

Mast diameter accepted:30mm to 62mm / Connector: N-J

Type:2x5/8wave C-Load(144MHz),5x5/8wave C-Load(430MHz),6x5/8wave C-Load(1200MHz),FRP outer shell