

4-Channel RX Power Splitter

DESCRIPTION

- Low power, compact 4-channel power splitter/combiner.
- The splitter covers the frequency range from 50–1000 MHz.
- Almost no ripple in loss and isolation over the entire frequency range.

SPECIFICATIONS

Electrical	
Frequency	50 - 1000 MHz
Insertion Loss	< 1.5 dB
Impedance	50 Ω
Isolation Between Outputs	> 20 dB
VSWR	< 1.3:1
Maximum Input Power	2 W
No. Of Channels	4

Mechanical	
Connection(s)	N(f)
Dimensions	89 x 39 x 29 mm
Weight	0.2 kg / 0.44 lb

Environmental	
Operating Temperature Range	-30 °C to +60 °C

ORDERING

Type	Product No.
PRO-RPS-4-N	210000593



DIAGRAM

INSERTION LOSS & ISOLATION

